



# KOLVER

## FAB & RAF SERIES TORQUE UP TO 3,8 NM

FAB series electric screwdrivers are our "best sellers" for the electronic industry. RAF series screwdrivers are designed to meet higher torque applications.

Their advanced ergonomic design, ease of use, high accuracy and durability have made these drivers the standard by which all others are measured. They are lightweight, compact, powerful and come standard with ESD-safe housing certified to SP method 2472 (Ericsson approved). These screwdrivers are available in an inline body style with either a lever start or push to start or in a pistol grip with a trigger start (also available with the cord coming out from the top - U option) and different speeds, for different assembly requirements.

The torque is set externally: an adjusting nut controls output torque by changing the clutch spring compression. A reference scale will indicate the torque setting. The low voltage 30 V DC rare earth motors combine high performances and long life. Replacing their carbon brushes once a year is all you need for maintenance.

The motor works in combination with a control unit. The electronic control circuit cuts the power supply to the motor in response to the clutch action, as soon as the pre-set torque has been reached.

In addition the controller can be supplied with torque reached signal, lever signal, remote start and reverse (see page of control units for all the details) and with ACE screw counter unit.

All FAB and RAF drivers come standard with ESD-safe body, suspension bail and 2.5 m connection cable. Spiral cable available on request.

The new heavy duty cables and connectors, developed for robotic applications, are made of antistatic dissipative material for a safe use in EPA environment.



Code	Model	Torque Nm	Screw size	RPM max	Start option	Weight kg	L x Ø mm	Housing option
110010/FR	FAB10RE/FR	0,05÷0,8	M2.5	1000	Lever	0,48	226x36	
110012/FR	FAB12RE/FR	0,2÷1,2	M3	1000	Lever	0,48	226x36	
112012/FR	FAB12PS/FR	0,2÷1,2	M3	1000	Push start	0,48	226x36	
110013/FR	FAB12PP/FR	0,2÷1,2	M3	1000	Lever	0,55	200x150x34	Pistol grip
110013/FR/U	FAB12PP/FR/U	0,2÷1,2	M3	1000	Lever	0,55	200x150x34	Pistol grip with top connector
110618/FR	FAB18RE/FR	0,3÷1,8	M4	650	Lever	0,48	226x36	
112618/FR	FAB18PS/FR	0,3÷1,8	M4	650	Push start	0,48	226x36	
110619/FR	FAB18PP/FR	0,3÷1,8	M4	650	Lever	0,55	200x150x34	Pistol grip
110619/FR/U	FAB18PP/FR/U	0,3÷1,8	M4	650	Lever	0,55	200x150x34	Pistol grip with top connector
120032/FR	RAF32NS/FR	0,7÷3,2	M5	1000	Lever	0,65	247x40	
122032/FR	RAF32PS/FR	0,7÷3,2	M5	1000	Push start	0,65	247x40	
120033/FR	RAF32PP/FR	0,7÷3,2	M5	1000	Lever	0,70	200x150x40	Pistol grip
120033/FR/U	RAF32PP/FR/U	0,7÷3,2	M5	1000	Lever	0,70	200x150x40	Pistol grip with top connector
120638/FR	RAF38NS/FR	0,9÷3,8	M5	650	Lever	0,65	247x40	
122638/FR	RAF38PS/FR	0,9÷3,8	M5	650	Push start	0,65	247x40	
120639/FR	RAF38PP/FR	0,9÷3,8	M5	650	Lever	0,70	200x150x40	Pistol grip
120639/FR/U	RAF38PP/FR/U	0,9÷3,8	M5	650	Lever	0,70	200x150x40	Pistol grip with top connector


# FAB & RAF SERIES



# KOLVER

# CONTROL UNITS

## CONTROL UNITS FAB & RAF SERIES



All Kolver screwdrivers work in combination with a control unit acting as an AC to DC transformer and torque controller. The electronic control circuit cuts the power supply to the motor as soon as the pre-set torque has been reached.

The EDU1FR control units for FAB and RAF screwdrivers feature a maintenance free state-of-the-art electronics with no wearing components with a circuit design suitable to both lever start and push start drivers with protection against current overload up to 10A. This design results in very low current to the driver's start switch and clutch switch to extend their life indefinitely. Additional features:

- Suitable to universal supply from 90 to 260 V ac 50/60 hz.
- Slow start (0-2 seconds) and RPM (60% to 100%).
- Visual indicators (green-red) for power on/off and clutch action.
- Reduced weight (0.6 kg) and compact size for easy placement.
- M12 waterproof connector with silver and gold contacts for perfect conductivity.

The EDU1FR/SG controller features additional circuits wired to one connector in the back panel: output 24V for torque reached and lever signals; input start and reverse contacts. A double output connector (DOCK01) is also available for operators using two screwdrivers on the same working area (only FAB and RAF series). One end of this device is to be connected to the controller (cable included), the other end to the drivers. The screwdrivers are not to be used at the same time.



ACE SCREW COUNTER



SOFT START AND SPEED REGULATION



SPIRAL CABLE



DOUBLE OUTPUT DEVICE WITH CABLE

Code	Model	Features	Dimensions mm	Weight kg	Screwdriver
010010/FR	EDU1FR	In: 90-260Vca out: 18-30Vcc power 120VA slow start and adjustable speed	138x118x67	0,600	All FAB and RAF
010010/FR/SG	EDU1FR/SG	Input: start and reverse contacts Output: torque reached & lever signal	138x118x67	0,600	All FAB and RAF

# **WESTEC**<sup>®</sup> - Sales & Services In India

Office No. 12, 1st Floor, Hermes Atrium,  
B wing, Plot 57, Sector – 11,  
CBD Belapur, Navi Mumbai – 400 614

Mob: 9821 0327 20 | Tel:+91-22-2756 6533  
Telefax: +91-22-2756 6534 | Website - <http://westec-india.com/>  
E-mail: [westecnavimumbai@vsnl.net](mailto:westecnavimumbai@vsnl.net)